

FIS GAS SENSOR SB-500-12

for CARBON MONOXIDE DETECTION

The SB-500-12 is a tin dioxide semiconductor gas sensor which has an excellent performance in CO detection. Using a mini-bead type sensing element with a periodic temperature change operation method, high sensitivity, selectively, small effect from humidity and other remarkable characteristics have been achieved. The SB-500-12 realizes the development of reliable CO detection devices.

Structure

Gas sensitive semiconductor material is a mini bead type and a heater coil and electrode wire are embedded in the element. The sensing element is installed in the metal housing which uses double stainless steel mesh (100 mesh) in the path of gas flow. This sensor unit is placed in an external housing which contains active charcoal filter (Fig 1c).

Operating conditions

When the sensor is operated with high/low periodic operation (Fig 2), sensor signal changes according to the temperature dependency characteristics. By detecting the sensor signal at sufficient timings, selective detection of CO has been achieved. Fig 3 shows the standard operation circuit and Fig 4 shows the sensitivity characteristics of the SB-500-12.




Fig 1a. Sensing element




Fig 1c. Pin Layout




Fig 1b. Configuration




Fig 1d. Equivalent circuit




Fig 2 SB-500-12: Operating conditions and output signal




Fig 3. Standard circuit




Fig 4. Sensitivity characteristics



Specifications

A. Standard Operating conditions

A: Standard Operating Conditions			
Symbol	Parameter	Specification	Conditions etc.
VH(H)	Heater voltage (high)	0.9 V ± 5%	AC, DC or pulse
VH(L)	Heater voltage (low)	0.2 V ± 5%	AC, DC or pulse
VC	Circuit voltage	Less than 5 V	DC: Pin2 (+) - Pin 1 (-)
RL	Load resistance	Variable (> 200 Ω)	PS < 10 mW
RH	Heater resistance	$2.8 \Omega \pm 0.2 \Omega$	at room temperature
TH(H)	Heating time (high)	$5 \sec \pm 0.1 \sec$	
TH(L)	Heating time (low)	20 sec ± 0.1 sec	
DT (L)	Detection timing (low)	< 0.1 秒	before switching to LOW
IS(H)	Current consumption(high)	132mA ± 15mA	VH=0.9V
IS(L)	Current consumption(low)	59mA ± 10mA	VH=0.2V
PS	Power dissipation of sensing element	Less than 10 mW	$P_{S} = \frac{(VC-VRL)^2}{R}$



Symbol	Parameter	Specification	Conditions etc.
Tao	Operating temperature	-10 °C to 50 °C	
Tas	Storage temp	-20 °C to 60 °C	
RH	Relative humidity	Less than 95% RH	
(O2)	Oxygen concentration	21% ± 1% (Standard condition)	Absolute minimum level: more than 18%
		The sensitivity characteristics are influenced by the variation in oxygen concentration. Please consult FIS for details.	

C. Sensitivity characteristics

Model	SB-500-12		
Symbol	Parameter	Specification	Conditions etc.
Rs	Sensor resistance	4.5kΩ-40 kΩ	at 1000ppm of CO
a (30-100)	Sensitivity slope (30-100 ppm)	1.05to2.1	log(Rs(30 ppm) /Rs(100ppm)) log(30/100)
a (100-300)	Sensitivity slope at (100-300 ppm)	0.5to1.0	log(Rs(300 ppm) /Rs(100ppm)) log(300/100)
Standard Test Conditions:		Temp: 20 °C \pm 2 °C VC: $5.0 \text{ V} \pm 5\%$ Humidity:65% \pm 5% VH: $0.9 \text{ V} \pm 5\%$ (in clean air) VH (low): $0.2 \text{ V} \pm 5\%$ RL: $10 \text{ k}\Omega \pm 1\%$ Pre-heating time: more than 48 hours	

D. Mechanical characteristics

211100110111001101101101101				
Items	Conditions	Specifications		
Vibration	Frequency: 5 - 500 Hz Acceleration: 1.3 G Sweep Time: 40 min.	Should satisfy the specifications shown in the sensitivity		
Drop	Height: 60 cm Number of impacts: 3 times	characteristics after test.		

Dimensions 1.Frame Droof mesh 2.Metal housing 3.Stainless steel mesh 10.0 ± 0.5 9.6 ± 0.5 4. Outside housing 5.Carbon filter 15.0 +1.0/ -0.3 6.Heater coil I 7. Sensing element 8.Lead wire 2.Metal housing 5.0 +0.3/-0.5 9.Plastic base 2.0 n 10. Electrode pin Production lot FIS1611-01 SB-500-12 ויוטעבו וזע. Scale: mm

Weight: 1.2g

E. Parts and Materials

No.	Parts	Materials
1	Flameproof mesh	SUS 316 (100 mesh, double)
2	Metal housing	Nickel plated brass
3	Stainless steel mesh	SUS 316 (100 mesh, single)
4	Outside housing	Nylon 6 (UL94 V-0)
5	Carbon filter	Activated carbon
6	Heater coil	Platinum
7	Sensing element	Tin dioxide
8	Lead wire	Platinum
9	Plastic base	PBT (poly butylen telephtalate)
10	Electrode pins	Iron-nickel alloy

Please contact MARCH, 2017

FIS Inc. 3-36-3,Kitazono Itami,Hyogo 664-0891 Japan

Tel: +81-72-780-1800 Fax: +81-72-785-0073 http://www.fisinc.co.jp

In the interest of continued product improvement, we reserve the right to change design features without prior